Configuring Dial-up software (FreePPP):

1. Select FreePPP Setup from the FreePPP folder, the pull down menu or Control Panels. Click on the right-facing arrow in the lower-left corner of the window to display the configuration panels (see cursor in the diagram below).

		FreePPP Setup	
A	Connect	Not connected. Click "Connect" to dial	0
	Connect to:	Untitled 🛛 🔻	
	From:	Home 🔻	
► N	Using:	Generic Modem 🔻)

2. On the General tab select Allow application to open connection, Check line state when connected, Show alerts during connect and disconnect.

	FreePPP Setup	
	Not connected. Click "Connect" to dial	
Connect to:	Untitled 🔻	
From:	Home 🔻	
♥ Using:	Generic Modem 🔻	
📓 General 🎼 Accounts 🗟 Locations 🗟 Modems		
🖂 Allow applications to open connection		
Disconnect if idle for 10 minutes 🔻		
🖾 Check line state when connected		
🖂 Show alerts during connect and disconnect		
🗌 On connect, open FreePPP Setup application		
🗌 Open application on connect		
Open TCP/IP		

3. Now click on the **Accounts** tab. Click **New**.

	FreePPP Setup 📃
Connect 2.6.2 Connect to:	Not installed or selected. Make sure FreePPP extension is installed and selected then restart.
From:	lane esd 🗢
v Using:	zoom 🗢
General General	counts 😹 Locations 😹 Modems Edit New Duplicate Delete

4. Enter FKBNet for Account name. Select Directly for Connect. Enter your User name and Password.

🛛 🎼 Account 🕅 🛣 Dialup 🗹 Options	
Account name:	FKBNet
Connect:	Directly 🗢
	Edit connection script
User name:	username
Password:	******
Reconnect automatically if connection drops	
	Cancel OK

5. In the **Dialup** tab, enter 441 for the **Area code** and 295-0099 for the **Phone number**. Click **OK**

🎼 Account 🕅 🛣 Dialup 🗹 Options		
Main Number:		
Area code:	441	
Phone number:	295-0099	
🔲 Dial area code	🔲 Dial as long distance	
Alternate Number 1:		
Area code:		
Phone number:		
🔲 Dial area code	🔲 Dial as long distance	
Alternate Number 2:		
Area code:		
Phone number:		
🔲 Dial area code	🔲 Dial as long distance	
	Cancel OK	

6. Select the **Options** tab. Enter 205.136.31.3 for the **Primary DNS** and 205.136.31.20 as the **Secondary DNS** address. Click **OK**. Save the changes.

🕼 Account 🕼 Dialup 🛛 Options	
Domain name:	
Primary DNS:	205.136.31.3
Secondary DNS:	205.136.31.20
🛛 Configure OT	TCP/IP for this Account
IP address: ⊚ f	Assigned by PPP server
0	0.0.0.0
	Cancel OK

7. Click the **Locations** tab. Click **Edit**.

	FreePPP Setup 📃
Connect	Not installed or selected. Make sure FreePPP extension is installed and selected then restart.
Connect to:	Untitled 🗢
From:	Home 🗢
v Using:	zoom 💠
General 🖟 Acc	Edit Edit Edit Duplicate Delete

8. If you have call waiting on the line, you should disable it by entering ***70**, in the **Dial prefix** box. If you need to dial a number to get an outside line you can enter it here as well. Otherwise, leave this box empty. Click **OK**.

FreePPP Location Configuration			
Location name:	Home		
Area code:	441		
Long distance prefix:			
When account area code does not match location area code:			
Dial long distance prefix before account area code 🗦			
Dial prefix:	*70,		
Long distance access code:	Cancel		
Dial suffix:	ОК		

Click on the square in the upper left-hand corner to dismiss the FreePPP setup window.