Windows XP DSL Setup Guide

1. Go to Control Panel and select Network and Internet Connections

🕏 Control Panel						🔲 🗗 🔀
Pån Edit View Pavarkes Table H	wip				_	
Control Panel 8	Pick a cat	egory				
Switch to Gaussic View	-		- 20			
See Also	See arance a	nd Thermos	Prode	re and Other Har	dware	
Windows Updates Windows Updates Windows Updates	www.com	nternet Cannections	99 1000	Accounts		
Options	To Add or Remov	e Programs	🤔 Data	Time, Language.	and Regional (ptions
	JO Sounds, Speed	h, and Audio Devices	<u>Č</u> , ****	sibility Options		
	🕘 Parlamance :	and Maintensance				
						We Computer
🛃 start 🔰 🖻 🔯 🔿 🗿	🈂 🔯 reo 🗿	2011 🐹 Mor	Box Spre	C Brys.	Dr Con	1000 640 1012 PM

2. Then click "Set Up Or Change Your Internet Connection"



3. A window should appear titled Internet Properties. Click the Add button.

ternet Prope	rties		?
General Securit	y Privacy Content	Connections	Programs Advance
To set Setup.	up an Internet connec	tion, click	Set <u>up</u>
Dial-up and V	irtual Private Network s	ettings	
			Add
			<u>R</u> emove
Choose Settin server for a c	igs if you need to conf onnection.	igure a proxy	Settings
Never dial	a <u>c</u> onnection		
O Dial <u>w</u> hen	ever a network connec	tion is not pres	ent
🔿 Always dia	al my default c <u>o</u> nnectioi	n	
Current	None		S <u>e</u> t Default
- Local Area Ne	etwork (LAN) settings –		
LAN Settings	do not apply to dial-up	connections.	LAN Settings
Choose Secu	igs above for dial-up s	eccings.	
	ОК	Ca	ncel Apply
<u>+</u>	ОК	Ca	ncel Apply

4. Select "Connect to the Internet via Broadband", and click next

New Connection Wizard	×
Type of Connection Select the type of the connection.	
Dial-up to private network. Connect using my phone line (modem or ISDN).	
Connect to a private network through the Internet. Create a Virtual Private Network (VPN) connection or tunnel through the	internet.
Connect directly to another computer. Connect using my serial, parallel, or infrared port.	
Connect to the network via broadband Connect through my broadband connection.	
K Back Next >	Cancel

5. Name the connection FKBDSL and click finish



6. On the following screen, type in your username and password, then click "Properties"

KBDSL Settings		? 🛿
Automatic configu Automatic configu use of manual se	uration uration may override manual set ttings, disable automatic configu	tings. To ensure the ration.
Automatically	detect settings	
Use automatio	configuration script	
Address		
Proxy server		
Use a proxy s apply to other Address;	erver for this connection (These r connections). Port: oxy server for local addresses	Advanced
Dial-up settings		
User name:	johndoe,@fkbdsl	Properties
Password:	•••••	Advanced
Domain:		
	ОК	

7. Under Service Name, type fkbdsl.bm, then click OK

🥯 FKBD	SL Prope	erties			? 🛛
General	Options	Security	Networking	Advanced	
Service	e name:				
fkbdsl.	bm				
Sho	w icon in r	notification	area when co	nnected	
-				ок	Cancel

8. If not already, make FKBDSL the default connection by selecting it and clicking "Set Default". Also, select "Always Dial My Default Connection". Then click OK. Setup is complete.

ternet Properties	?
General Security Privacy Content Connection	ns Programs Advanced
To set up an Internet connection, click Setup.	Setup
Dial-up and Virtual Private Network settings	1
FKBDSL (Default)	A <u>d</u> d
	<u>R</u> emove
Choose Settings if you need to configure a prox server for a connection.	Y <u>S</u> ettings
O Never dial a connection	
Dial whenever a network connection is not preserved.	resent
Always dial my default connection	
Current FKBDSL	S <u>e</u> t Default
- Local Area Network (LAN) settings	
LAN Settings do not apply to dial-up connections Choose Settings above for dial-up settings.	5. LAN Settings
	Cancel Apoly